

SPERAS M2R Mini Pocket Thrower NewsLetter

Model No.	M2R-35								
Application	Headlamp,Outdoor flashlight, EDC flashlight, household								
Lifespan	Over 50,000hrs								
LED	OSRAM LED								
Circuit	Flick-free circuit,memory function								
Batteries	1*18350 Battery								
Voltage	2.5-8.4V								
Material	T6061 aircraft-grade Aluminum Alloy								
Reflector	Aluminum reflector								
Lens	Orange Aluminium Reflector								
Appearance	Black Finish								
Switch	Good Feel Side Switch with power indicator								
Waterproof	IP68, Anti-dust,living water and rain proof								
Dimension	1.08"(Head dia)*0.88"(Body dia.)*2.99"(length) 27.5(Head dia.) *22.5(Body dia.)*76(Length)mm								
Weight	115g/4.06oz(include battery)								
Package	Standard hang box								
IN THE BOX	1*M2R-35, 1*18650 battery(Optional) 1*Type-C cable 1* Headlamp strap accessories 1*Lanyard, 2*Spare O-ring, 1* User manual								
SPERAS M4	High	Medium	Low	Eco	Strobe	SOS	Retail price (USD)		Wholesale price (USD)
Output Lumens	1200LM	400LM	100LM	5LM	1200LM	100LM	US\$53.69		
Beam Distance	125M	73M	40M	14M	\	\			
Beam Intensity (cd)	3900cd	1350cd	400cd	51cd	\	\			
Running Time	90s+0.5h	1.5h	5.86h	65h					

Features/Pros

- Right-angle flashlight.** You could use as a handheld flashlight; You can also use as a powerful headlamp.
- High performance.**Equipped with OSRAM led AND advanced circuit design, M2R-35 has 1200lm max output and 6 various modes for your different usage.
- USB-C charging** , take **about 2Hrs** to complete charging
- Free Your hand:** The tail of the M2R-35 has magnet function, which could free you hand as a working lamp.
- 4-Steps power indicator system** for optimal charge and power status indication.
Green>70%,Orange>30% Red>10% red flash>1%
- High efficient circuit, **flicker-free**, and a **max of 65hrs.** runtime in **5lumen Eco** mode.
- Lock function** to avoid unintended operation.
- Competitive price and 5 years warranty**
- It is a reliable and powerful flashlight for multiple applications.

RIGHT-ANGLE USB-C FLASHLIGHT



LOCK FUNCTION

The lock function is designed to avoid the false trigger
Safe for carry and travel



Long Press 2s, Lock the light
Eco first, then flicker 2 times to indicate entering LOCK
In the LOCK state, the flashlight can't be operated



In LOCK State, click "3 times to UNLOCK the light
Flicker 2 times to indicate the flashlight UNLOCK



USB-C FAST CHARGING



Charging Time

- When in charge
- When full in charge
- Problem state when in charge

SPERAS M2R

Use as a headlamp

Use as a handheld Flashlight

Magnet tail, use a work light, free hand

MULTIPLE USAGE

Inside the box

1x M2R-35	1x 18350 battery	2x O-rings	1x Headlamp strap accessories
1x Type-C cable	1x Lanyard	1x Manual	